

Package ‘sRACIPE’

November 15, 2024

Type Package

Title Systems biology tool to simulate gene regulatory circuits

Version 1.22.0

Description sRACIPE implements a randomization-based method for gene circuit modeling. It allows us to study the effect of both the gene expression noise and the parametric variation on any gene regulatory circuit (GRC) using only its topology, and simulates an ensemble of models with random kinetic parameters at multiple noise levels. Statistical analysis of the generated gene expressions reveals the basin of attraction and stability of various phenotypic states and their changes associated with intrinsic and extrinsic noises. sRACIPE provides a holistic picture to evaluate the effects of both the stochastic nature of cellular processes and the parametric variation.

License MIT + file LICENSE

Encoding UTF-8

Suggests knitr, BiocStyle, rmarkdown, tinytest, doFuture

VignetteBuilder knitr

LinkingTo Rcpp

biocViews ResearchField, SystemsBiology, MathematicalBiology,
GeneExpression, GeneRegulation, GeneTarget

Depends R (>= 3.6.0), SummarizedExperiment, methods, Rcpp

Imports ggplot2, reshape2, MASS, RColorBrewer, gridExtra, visNetwork,
gplots, umap, htmlwidgets, S4Vectors, BiocGenerics, grDevices,
stats, utils, graphics

RoxygenNote 7.1.0

URL <https://vivekkohar.github.io/sRACIPE/>,
<https://github.com/vivekkohar/sRACIPE>, <https://geneex.jax.org/>

BugReport <https://github.com/vivekkohar/sRACIPE/issues>

git_url <https://git.bioconductor.org/packages/sRACIPE>

git_branch RELEASE_3_20

git_last_commit 9d5538c

git_last_commit_date 2024-10-29

Repository Bioconductor 3.20

Date/Publication 2024-11-14

Author Vivek Kohar [aut, cre] (<<https://orcid.org/0000-0003-1813-1597>>),
Mingyang Lu [aut]

Maintainer Vivek Kohar <vivek.kohar@gmail.com>

Contents

| | |
|-----------------------------------|-----------|
| .loadNetworkFile | 2 |
| .ModelPvalue | 3 |
| .NthMin | 4 |
| .PermutedVar | 4 |
| .SimulatedPValueAbs | 5 |
| .SimulatedVarPValue | 5 |
| annotation,RacipeSE-method | 6 |
| annotation<- ,RacipeSE,ANY-method | 6 |
| configData | 7 |
| CoupledToggleSwitchSA | 7 |
| demoCircuit | 8 |
| densityPlot | 8 |
| EMT1 | 9 |
| EMT2 | 9 |
| RacipeSE | 10 |
| RacipeSE-class | 11 |
| sRACIPE | 11 |
| sracipeCircuit | 12 |
| sracipeCircuit<- | 13 |
| sracipeConfig | 14 |
| sracipeConfig<- | 14 |
| sracipeGenParamNames | 15 |
| sracipeGetTS | 15 |
| sracipeHeatmapSimilarity | 16 |
| sracipeIC | 17 |
| sracipeIC<- | 18 |
| sracipeKnockDown | 19 |
| sracipeNormalize | 20 |
| sracipeOverExp | 21 |
| sracipeParams | 22 |
| sracipeParams<- | 23 |
| sracipePlotCircuit | 23 |
| sracipePlotData | 24 |
| sracipePlotParamBifur | 26 |
| sracipeSimulate | 27 |
| Index | 31 |

| | |
|------------------|---|
| .loadNetworkFile | <i>Loads the network/topology file.</i> |
|------------------|---|

Description

The network file should contain three columns with headers, "Source" "Target" "Type" Here "Source" and "Target" are the names of the genes and "Type" refers to the regulation, "1" if source activates target and "2" if source inhibits target.

Usage

```
.loadNetworkFile(networkFile = "inputs/test.net")
```

Arguments

networkFile Network file name

Value

Network as a dataframe

| | |
|--------------|---|
| .ModelPvalue | <i>Returns the variance array after permutations.</i> |
|--------------|---|

Description

A utility function.

Usage

```
.ModelPvalue(  
  dataSimulation,  
  dataReference,  
  clusterCut,  
  permutations,  
  refClusterVar,  
  corMethod,  
  simulatedClusterVar  
)
```

Arguments

dataSimulation Simulation data to be compared.
dataReference Reference data with which to compare.
clusterCut The original cluster assignments.
permutations The number of permutations.
refClusterVar SD of the clusters.
corMethod Correlation method to be used.
simulatedClusterVar
 Variance of simulated clusters

Value

An array of dimension n.models by nClusters by permutations.

`.NthMin` *Find nth minimum value from a vector*

Description

A utility function to find the nth minimum

Usage

```
.NthMin(x, index)
```

Arguments

| | |
|--------------------|---------------------------|
| <code>x</code> | the given unsorted vector |
| <code>index</code> | N. |

Value

the nth minimum element of the vector

`.PermutedVar` *Find variance of permutations*

Description

A utility function to generate permutations

Usage

```
.PermutedVar(simulated.refCor, clusterCut, permutations, refClusterVar)
```

Arguments

| | |
|-------------------------------|--|
| <code>simulated.refCor</code> | Correlation matrix of simulated and reference data |
| <code>clusterCut</code> | The original cluster assignments |
| <code>permutations</code> | The number of permutations |
| <code>refClusterVar</code> | Reference Cluster Variance |

Value

An array of dimension n.models by nClusters by permutations

.SimulatedPValueAbs *Finds the variance corresponding to a given value.*

Description

A utility function to calculate the absolute p values.

Usage

```
.SimulatedPValueAbs(permutedVar, simulatedClusterVar)
```

Arguments

permutedVar An array containing the distance of clusters for each model for every permutation.
simulatedClusterVar Variance of simulated clusters

Value

p-values for each model.

.SimulatedVarPValue *Finds the variance corresponding to a given value.*

Description

A utility function for calculating the p values.

Usage

```
.SimulatedVarPValue(permutedVar, pValue)
```

Arguments

permutedVar An array containing the distance of clusters for each model for every permutation.
pValue Cut off p vlaue.

Value

p-values for each model.

annotation,RacipeSE-method

A method to get the annotation

Description

A method to get the annotation

Usage

```
## S4 method for signature 'RacipeSE'
annotation(object, ...)
```

Arguments

| | |
|--------|--|
| object | RacipeSE object |
| ... | Additional arguments, for use in specific methods. |

Value

character

Examples

```
data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 100)
ann <- annotation(rSet)
annotation(rSet) <- ann
```

annotation<-,RacipeSE,ANY-method

A method to set the circuit name or annotation

Description

A method to set the circuit name or annotation

Usage

```
## S4 replacement method for signature 'RacipeSE,ANY'
annotation(object, ...) <- value
```

Arguments

| | |
|--------|--|
| object | RacipeSE object |
| ... | Additional arguments, for use in specific methods. |
| value | annotation character |

Value

A RacipeSE object

Examples

```
data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 100)
ann <- annotation(rSet)
annotation(rSet) <- ann
```

 configData

Configuration Data

Description

It contains simulation parameters like integration method (stepper) and other lists or vectors like simParams, stochParams, hyperParams, options, thresholds etc. The list simParams contains values for parameters like the number of models (numModels), simulation time (simulationTime), step size for simulations (integrateStepSize), when to start recording the gene expressions (printStart), time interval between recordings (printInterval), number of initial conditions (nIC), output precision (outputPrecision), tolerance for adaptive runge kutta method (rkTolerance), parametric variation (paramRange). The list stochParams contains the parameters for stochastic simulations like the number of noise levels to be simulated (nNoise), the ratio of subsequent noise levels (noiseScalingFactor), maximum noise (initialNoise), whether to use same noise for all genes or to scale it as per the median expression of the genes (scaledNoise), ratio of shot noise to additive noise (shotNoise). The list hyperParams contains the parameters like the minimum and maximum production and degradation of the genes, fold change, hill coefficient etc. The list options includes logical values like annealing (anneal), scaling of noise (scaledNoise), generation of new initial conditions (genIC), parameters (genParams) and whether to integrate or not (integrate). The user modifiable simulation options can be specified as other arguments. This list should be used if one wants to modify many settings for multiple simulations.

Usage

```
configData
```

Format

```
list
```

 CoupledToggleSwitchSA *Five coupled toggle switches*

Description

This data contains the topology of a circuit with ten genes A1...A5 and B1...B5. Genes with different alphabet inhibit each other whereas genes from different groups activate the other. For further details, see Kohar, V. and Lu, M., Role of noise and parametric variation in the dynamics of gene regulatory circuits, npj Systems Biology and Applications 4, Article number: 40 (2018)

Usage

```
CoupledToggleSwitchSA
```

Format

A data frame with 18 rows and 3 variables

| | |
|-------------|---|
| demoCircuit | <i>A toggle switch circuit for demonstrations</i> |
|-------------|---|

Description

This data contains the topology of a circuit with two genes A and B both of which inhibit each other and have self activations. For further details, see Kohar, V. and Lu, M., Role of noise and parametric variation in the dynamics of gene regulatory circuits, npj Systems Biology and Applications 4, Article number: 40 (2018)

Usage

```
demoCircuit
```

Format

A data frame with 4 rows and 3 variables

| | |
|-------------|---------------------|
| densityPlot | <i>Density Plot</i> |
|-------------|---------------------|

Description

Plot the density of points as an image alongwith histograms on the sides.

Usage

```
densityPlot(plotData, binCount = 40, plotColor = NULL, ...)
```

Arguments

| | |
|-----------|--|
| plotData | Dataframe containing the data. |
| binCount | (optional) Integer. Default 40. The number of bins to be used for dividing the data along an axis. |
| plotColor | (optional) The color palette. |
| ... | any additional arguments |

Value

```
plot
```

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#), [sracipeHeatmapSimilarity](#)

EMT1

A circuit for epithelial to mesenchymal transition

Description

This data contains the topology of a circuit with sixteen genes involved in EMT. For further details, see Kohar, V. and Lu, M., Role of noise and parametric variation in the dynamics of gene regulatory circuits, npj Systems Biology and Applications 4, Article number: 40 (2018)

Usage

EMT1

Format

A data frame with 59 rows and 3 variables

EMT2

A circuit for epithelial to mesenchymal transition including microRNAs

Description

This data contains the topology of a circuit with twenty two nodes including micro RNAs involved in EMT. For further details, see Huang et al., Interrogating the topological robustness of gene regulatory circuits by randomization, PLoS computational biology 13 (3), e1005456

Usage

EMT2

Format

A data frame with 82 rows and 3 variables

Description

Create an `RacipeSE` object. `RacipeSE` is an S4 class for Random Circuit Perturbation (RACIPE) simulations of networks in which a large number of models with randomized parameters are used for simulation of the circuit. Each model can be considered as a sample. It extends the `SummarizedExperiment` class to store and access the circuit, simulated gene expressions, parameters, initial conditions and other meta information. `SummarizedExperiment` slot assays is used for storing simulated gene expressions. The rows of these matrix-like elements correspond to various genes in the circuit and columns correspond to models. The first element is used for unperturbed deterministic simulations. The subsequent elements are used for stochastic simulations at different noise levels and/or knockout simulations. `SummarizedExperiment` slot `rowData` stores the circuit topology. It is a square matrix with dimension equal to the number of genes in the circuit. The values of the matrix represent the type of interaction in the gene pair given by row and column. 1 represents activation, 2 inhibition and 0 no interaction. This should not be set directly and `sracipeCircuit` accessor should be used instead. `SummarizedExperiment` slot `colData` contains the parameters and initial conditions for each model. Each gene in the circuit has two parameters, namely, its production rate and its degradation rate. Each interaction in the has three parameters, namely, threshold of activation, the hill coefficient, and the fold change. Each gene has one or more initial gene expression values as specified by `nIC`. This should not be modified directly and `sracipeParams` and `sracipeIC` accessors should be used instead. `SummarizedExperiment` slot `metadata` Contains metadata information especially the config list (containing the simulation settings), annotation, `nInteraction` (number of interactions in the circuit), `normalized` (whether the data is normalized or not), data analysis lists like `pca`, `umap`, cluster assignment of the models etc. The config list includes simulation parameters like integration method (`stepper`) and other lists or vectors like `simParams`, `stochParams`, `hyperParams`, `options`, `thresholds` etc. The list `simParams` contains values for parameters like the number of models (`numModels`), simulation time (`simulationTime`), step size for simulations (`integrateStepSize`), when to start recording the gene expressions (`printStart`), time interval between recordings (`printInterval`), number of initial conditions (`nIC`), output precision (`outputPrecision`), tolerance for adaptive runge kutta method (`rkTolerance`), parametric variation (`paramRange`). The list `stochParams` contains the parameters for stochastic simulations like the number of noise levels to be simulated (`nNoise`), the ratio of subsequent noise levels (`noiseScalingFactor`), maximum noise (`initialNoise`), whether to use same noise for all genes or to scale it as per the median expression of the genes (`scaledNoise`), ratio of shot noise to additive noise (`shotNoise`). The list `hyperParams` contains the parameters like the minimum and maximum production and degradation of the genes, fold change, hill coefficient etc. The list `options` includes logical values like `annealing` (`anneal`), scaling of noise (`scaledNoise`), generation of new initial conditions (`genIC`), parameters (`genParams`) and whether to integrate or not (`integrate`). The user modifiable simulation options can be specified as arguments to `sracipeSimulate` function.

Usage

```
RacipeSE(
  .object = NULL,
  assays = SimpleList(),
  rowData = NULL,
  colData = DataFrame(),
  metadata = list(),
  ...
)
```

)

Arguments

.object (optional) Another RacipeSE object.
 assays (optional) assay object for initialization
 rowData (optional) rowData for initialization
 colData (optional) colData for initialization
 metadata (optional) metadata for initialization
 ... Arguments passed to SummarizedExperiment

Value

RacipeSE object

Examples

```
rSet <- RacipeSE()
```

| | |
|----------------|-----------------|
| RacipeSE-class | <i>RacipeSE</i> |
|----------------|-----------------|

Description

An S4 class for Random Circuit Perturbation (RACIPE) simulations of networks. Extends the [SummarizedExperiment](#) class. RACIPE can simulate a gene regulatory circuit using the circuit and a large ensemble of parameters.

| | |
|---------|---|
| sRACIPE | <i>sRACIPE: A package for stochastic random circuit perturbation.</i> |
|---------|---|

Description

sRACIPE is a systems biology tool to study the role of noise and parameter variation in gene regulatory circuits. It implements a randomization-based method for gene circuit modeling. It allows us to study the effect of both the gene expression noise and the parametric variation on any gene regulatory circuit (GRC) using only its topology, and simulates an ensemble of models with random kinetic parameters at multiple noise levels. Statistical analysis of the generated gene expressions reveals the basin of attraction and stability of various phenotypic states and their changes associated with intrinsic and extrinsic noises. sRACIPE provides a holistic picture to evaluate the effects of both the stochastic nature of cellular processes and the parametric variation.

sRACIPE functions

[sracipeSimulate](#) Primary function to simulate a circuit. Contains options for plotting as well.
[sracipeKnockDown](#) In-silico knockdown analysis of the circuit. Plots the relative changes in different cluster proportions.

[sracipeOverExp](#) In-silico over expression analysis of the circuit. Plots the relative changes in different cluster proportions.

[sracipePlotData](#) Plot the simulated data. Includes options to plot the hierarchical clustering analysis, principal components, and uniform manifold approximation and projection. Can plot the stochastic as well as the knockout simulations.

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#)

| | |
|----------------|----------------------------------|
| sracipeCircuit | <i>Method to get the circuit</i> |
|----------------|----------------------------------|

Description

The circuit file should contain three columns with headers, "Source" "Target" "Type" Here "Source" and "Target" are the names of the genes and "Type" refers to the regulation, "1" if source activates target and "2" if source inhibits target.

Usage

```
sracipeCircuit(.object)

## S4 method for signature 'RacipeSE'
sracipeCircuit(.object)
```

Arguments

.object RacipeSE object

Value

A dataframe

Examples

```
rs <- RacipeSE()
data("demoCircuit")
sracipeCircuit(rs) <- demoCircuit
circuitDataFrame <- sracipeCircuit(rs)
rm(rs, demoCircuit, circuitDataFrame)
```

```
sracipeCircuit<-      Initialize the circuit
```

Description

Initialize the circuit from a topology file or a data.frame A typical topology file looks like

| Source | Target | Type |
|--------|--------|------|
| geneA | geneB | 2 |
| geneB | geneC | 1 |
| geneB | geneA | 2 |

Here the regulation type is specified by number - activation: 1, inhibition: 2

Usage

```
sracipeCircuit(.object) <- value

## S4 replacement method for signature 'RacipeSE'
sracipeCircuit(.object) <- value
```

Arguments

| | |
|---------|---|
| .object | RacipeSE object |
| value | data.frame containing the circuit information |

Value

data.frame

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#)

Examples

```
RacipeSet <- RacipeSE()
data("demoCircuit")
sracipeCircuit(RacipeSet) <- demoCircuit
sracipeCircuit(RacipeSet)
rm(RacipeSet, demoCircuit)
```

| | |
|---------------|--|
| sracipeConfig | <i>A method to access the simulation hyperparameters</i> |
|---------------|--|

Description

The hyperparameters like number of models, range from which parameters are to be sampled, simulation time etc.

Usage

```
sracipeConfig(.object)

## S4 method for signature 'RacipeSE'
sracipeConfig(.object)
```

Arguments

.object RacipeSE object

Value

list

Examples

```
RacipeSet <- RacipeSE()
data("demoCircuit")
sracipeCircuit(RacipeSet) <- demoCircuit
sracipeConfig(RacipeSet)
rm(RacipeSet)
```

| | |
|-----------------|--|
| sracipeConfig<- | <i>A method to access the simulation hyperparameters</i> |
|-----------------|--|

Description

The hyperparameters like number of models, range from which parameters are to be sampled, simulation time etc.

Usage

```
sracipeConfig(.object) <- value

## S4 replacement method for signature 'RacipeSE'
sracipeConfig(.object) <- value
```

Arguments

.object RacipeSE object
value list. Configuration as a list

Value

RacipeSE object

Examples

```
rSet <- RacipeSE()
tmpConfig <- sracipeConfig(rSet)
sracipeConfig(rSet) <- tmpConfig
rm(rSet, tmpConfig)
```

sracipeGenParamNames *Generate parameter names for a circuit*

Description

Generate parameter names for a circuit

Usage

```
sracipeGenParamNames(circuit = "inputs/test.tpo")
```

Arguments

circuit RacipeSE object or topology as data.frame or filename

Value

list

Examples

```
rSet <- RacipeSE()
data("demoCircuit")
sracipeCircuit(rSet) <- demoCircuit
paramNames <- sRACIPE::sracipeGenParamNames(rSet)
```

sracipeGetTS *A method to extract the time series*

Description

If timeSeries option is used in sracipeSimulate function, this method will return the simulated time series.

Usage

```
sracipeGetTS(.object)

## S4 method for signature 'RacipeSE'
sracipeGetTS(.object)
```

Arguments

.object RacipeSE object

Value

List

Examples

```
data("demoCircuit")
RacipeSet <- RacipeSE()
sracipeCircuit(RacipeSet) <- demoCircuit
RacipeSet <- sracipeSimulate(demoCircuit, timeSeries = TRUE,
simulationTime = 2)
trajectories <- sracipeGetTS(RacipeSet)
rm(RacipeSet)
```

sracipeHeatmapSimilarity

Calculates the similarity between two gene expression data.

Description

Comparison is done across columns, i.e., how similar are the columns in the two dataset. For gene expression data, format data so that gene names are in rows and samples in columns.

Usage

```
sracipeHeatmapSimilarity(
  dataReference,
  dataSimulation,
  clusterCut = NULL,
  nClusters = 3,
  pValue = 0.05,
  permutedVar,
  permutations = 1000,
  corMethod = "spearman",
  clusterMethod = "ward.D2",
  method = "pvalue",
  buffer = 0.001,
  permutMethod = "simulation",
  returnData = FALSE
)
```

Arguments

dataReference Matrix. The reference data matrix, for example, the experimental gene expression values

dataSimulation Matrix. The data matrix to be compared.

clusterCut (optional) Integer vector. Clsuter numbers assigned to reference data. If clusterCut is missing, hierarchical clustering using /codeward.D2 and /codedistance = (1-cor(x, method = "spear"))/2 will be used to cluster the reference data.

| | |
|---------------|---|
| nClusters | (optional) Integer. The number of clusters in which the reference data should be clustered for comparison. Not needed if clusterCut is provided. |
| pValue | (optional) Numeric. p-value to consider two gene expression sets as belonging to same cluster. Ward's method with spearman correlation is used to determine if a model belongs to a specific cluster. |
| permutedVar | (optional) Similarity scores computed after permutations. |
| permutations | (optional) Integer. Default 1000. Number of gene permutations to generate the null distribution. |
| corMethod | (optional) Correlation method. Default method is "spearman". For single cell data, use "kendall" |
| clusterMethod | (optional) Character - default ward.D2, other options include complete. Clustering method to be used to cluster the experimental data. hclust for other options. |
| method | (optional) character. Method to compare the gene expressions. Default pvalue. One can use variance as well which assigns clusters based on the cluster whose samples have minimum variance with the simulated sample. |
| buffer | (optional) Numeric. Default 0.001. The fraction of models to be assigned to clusters to which no samples could be assigned. For example, a minimum of 1 ghost sample in reference is assigned to NULL cluster. |
| permutMethod | "sample" or "reference" |
| returnData | (optional) Logical. Default FALSE. Whether to return the sorted and clustered data. |

Value

A list containing the KL distance of new cluster distribution from reference data and the probability of each cluster in the reference and simulated data.

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#), [sracipeHeatmapSimilarity](#)

| | |
|-----------|--|
| sracipeIC | <i>A method to get the initial conditions used for simulations</i> |
|-----------|--|

Description

The initial conditions of each of the models.

Usage

```
sracipeIC(.object)

## S4 method for signature 'RacipeSE'
sracipeIC(.object)
```

Arguments

.object RacipeSE object

Value

DataFrame

Examples

```
data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 20,
integrate=FALSE)
ics <- sracipeIC(rSet)
rm(rSet,ics)
```

sracipeIC<-

A method to set the initial conditions

Description

Set the initial conditions

Usage

```
sracipeIC(.object) <- value

## S4 replacement method for signature 'RacipeSE'
sracipeIC(.object) <- value
```

Arguments

| | |
|---------|---|
| .object | RacipeSE object |
| value | DataFrame containing the initial conditions |

Value

A RacipeSE object

Examples

```
data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 10,
integrate=FALSE)
ics <- sracipeIC(rSet)
sracipeIC(rSet) <- ics
rm(rSet, ics)
```

| | |
|-------------------------------|---|
| <code>sracipeKnockDown</code> | <i>Perform in-silico knockdown analysis</i> |
|-------------------------------|---|

Description

Calculate the fraction of models in different clusters with full parameter range and on a subset of models with low production rate of a specific gene representing the knockdown of the specific gene.

Usage

```
sracipeKnockDown(
  .object,
  reduceProduction = 10,
  nClusters = 2,
  clusterOfInterest = 2,
  plotFilename = NULL,
  plotHeatmap = TRUE,
  plotBarPlot = TRUE,
  clusterCut = NULL,
  plotToFile = FALSE
)

## S4 method for signature 'RecipeSE'
sracipeKnockDown(
  .object,
  reduceProduction = 10,
  nClusters = 2,
  clusterOfInterest = 2,
  plotFilename = NULL,
  plotHeatmap = TRUE,
  plotBarPlot = TRUE,
  clusterCut = NULL,
  plotToFile = FALSE
)
```

Arguments

| | |
|--------------------------------|--|
| <code>.object</code> | RecipeSE object generated by <code>sracipeSimulate</code> function. |
| <code>reduceProduction</code> | (optional) Percentage to which production rate decreases on knockdown. Uses a default value of 10 percent. |
| <code>nClusters</code> | (optional) Number of clusters in the data. Uses a default value of 2. |
| <code>clusterOfInterest</code> | (optional) cluster number (integer) to be used for arranging the transcription factors |
| <code>plotFilename</code> | (optional) Name of the output file. |
| <code>plotHeatmap</code> | logical. Default TRUE. Whether to plot the heatmap or not. |
| <code>plotBarPlot</code> | logical. Default TRUE. Whether to plot the barplot. |
| <code>clusterCut</code> | integer or character. The cluster assignments. |
| <code>plotToFile</code> | logical. Default FALSE. |

Value

List containing fraction of models in different clusters in the original simulations and after knocking down different genes. Additionally, it generates two pdf files in the results folder. First is barplot showing the percentage of different clusters in the original simulations and after knocking down each gene. The second pdf contains the heatmap of clusters after marking the models with cluster assignments.

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#)

Examples

```
data("demoCircuit")
## Not run:
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 100,
plots=FALSE, plotToFile = FALSE)
rSet <- sRACIPE::sracipeNormalize(rSet)
rSet <- sRACIPE::sracipeKnockDown(rSet, plotToFile = FALSE,
plotBarPlot = TRUE, plotHeatmap = FALSE, reduceProduction = 50)

## End(Not run)
```

| | |
|------------------|--|
| sracipeNormalize | <i>Normalize the simulated gene expression</i> |
|------------------|--|

Description

Normalize the simulated gene expression including gene expressions for stochastic and knockout simulations

Usage

```
sracipeNormalize(.object)

## S4 method for signature 'RacipeSE'
sracipeNormalize(.object)
```

Arguments

.object RacipeSE object

Value

A RacipeSE object

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#),

Examples

```
data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 20,
integrateStepSize = 0.1, simulationTime = 30)
rSet <- sracipeNormalize(rSet)
```

| | |
|----------------|---|
| sracipeOverExp | <i>Perform in-silico over expression analysis</i> |
|----------------|---|

Description

Calculates the fraction of models in different clusters with full parameter range and on a subset of models with high production rate of a specific gene representing the over expression of the specific gene.

Usage

```
sracipeOverExp(
  .object,
  overProduction = 10,
  nClusters = 2,
  clusterOfInterest = 2,
  plotFilename = NULL,
  plotHeatmap = TRUE,
  plotBarPlot = TRUE,
  clusterCut = NULL,
  plotToFile = FALSE
)

## S4 method for signature 'RacipeSE'
sracipeOverExp(
  .object,
  overProduction = 10,
  nClusters = 2,
  clusterOfInterest = 2,
  plotFilename = NULL,
  plotHeatmap = TRUE,
  plotBarPlot = TRUE,
  clusterCut = NULL,
  plotToFile = FALSE
)
```

Arguments

| | |
|--------------------------------|--|
| <code>.object</code> | RacipeSE object generated by <code>sracipeSimulate</code> function. |
| <code>overProduction</code> | (optional) Percentage to which production rate decreases on knockdown. Uses a default value of 10 percent. |
| <code>nClusters</code> | (optional) Number of clusters in the data. Uses a default value of 2. |
| <code>clusterOfInterest</code> | (optional) cluster number (integer) to be used for arranging the transcription factors |

plotFilename (optional) Name of the output file.
 plotHeatmap logical. Default TRUE. Whether to plot the heatmap or not.
 plotBarPlot logical. Default TRUE. Whether to plot the barplot.
 clusterCut integer or character. The cluster assignments.
 plotToFile logical. Default FALSE.

Value

List containing fraction of models in different clusters in the original simulations and after knocking down different genes. Additionally, it generates two pdf files in the results folder. First is barplot showing the percentage of different clusters in the original simulations and after knocking down each gene. The second pdf contains the heatmap of clusters after marking the models with cluster assignments.

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#),

Examples

```

data("demoCircuit")
## Not run:
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 100,
plots=FALSE, plotToFile = FALSE)
rSet <- sRACIPE::sracipeNormalize(rSet)

## End(Not run)

```

sracipeParams

A method to access the simulation parameters

Description

The parameters for each model.

Usage

```

sracipeParams(.object)

## S4 method for signature 'RecipeSE'
sracipeParams(.object)

```

Arguments

.object RecipeSE object

Value

A data.frame

Examples

```

data("demoCircuit")
RacipeSet <- sracipeSimulate(demoCircuit, integrate = FALSE, numModels=20)
parameters <- sracipeParams(RacipeSet)
sracipeParams(RacipeSet) <- parameters
rm(parameters,RacipeSet)

```

sracipeParams<- *A method to set the simulation parameters*

Description

Set the parameters

Usage

```

sracipeParams(.object) <- value

## S4 replacement method for signature 'RacipeSE'
sracipeParams(.object) <- value

```

Arguments

| | |
|---------|-------------------------------------|
| .object | RacipeSE object |
| value | DataFrame containing the parameters |

Value

A RacipeSE object

Examples

```

data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 20,
integrate = FALSE)
parameters <- sracipeParams(rSet)
sracipeParams(rSet) <- parameters
rm(parameters, rSet)

```

sracipePlotCircuit *Plot Gene Regulatory Circuit*

Description

Plot Gene Regulatory Circuit to a file or output device.

Usage

```

sracipePlotCircuit(.object, plotToFile = FALSE)

## S4 method for signature 'RacipeSE'
sracipePlotCircuit(.object, plotToFile = TRUE)

```

Arguments

.object RaciPE object A list returned by [sracipeSimulate](#) function
 plotToFile (optional) logical. Default FALSE. Whether to save plots to a file.

Value

circuit plot

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#)

Examples

```
data("demoCircuit")
## Not run:
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 20,
integrateStepSize = 0.1, simulationTime = 30)
sracipePlotCircuit(rSet, plotToFile = FALSE)
rm(rSet)

## End(Not run)
```

 sracipePlotData

Plot sRACIPE data

Description

Plots heatmap, pca, umap of the data simulated using sRACIPE

Usage

```
sracipePlotData(
  .object,
  plotToFile = FALSE,
  nClusters = 2,
  heatmapPlot = TRUE,
  pcaPlot = TRUE,
  umapPlot = TRUE,
  networkPlot = TRUE,
  clustMethod = "ward.D2",
  col = col,
  distType = "euclidean",
  assignedClusters = NULL,
  corMethod = "spearman",
  ...
)

## S4 method for signature 'RaciPE'
sracipePlotData(
  .object,
```



```

    plotToFile = FALSE,
    nClusters = 2,
    heatmapPlot = TRUE,
    pcaPlot = TRUE,
    umapPlot = TRUE,
    networkPlot = TRUE,
    clustMethod = "ward.D2",
    col = col,
    distType = "euclidean",
    assignedClusters = NULL,
    corMethod = "spearman",
    ...
  )

```

Arguments

| | |
|------------------|--|
| .object | List A list returned by sracipeSimulate function |
| plotToFile | (optional) logical. Default FALSE. Whether to save plots to a file. |
| nClusters | (optional) Integer. Default 2. Expected number of clusters in the simulated data. Hierarchical clustering will be used to cluster the data and the the models will be colored in UMAP and PCA plots according to these clustering results. The clusters can be also supplied using <code>assignedClusters</code> . |
| heatmapPlot | (optional) logical. Default TRUE. Whether to plot hierarchichal clustering. |
| pcaPlot | (optional) logical. Default TRUE. Whether to plot PCA embedding. |
| umapPlot | (optional) logical. Default TRUE. Whether to plot UMAP embedding |
| networkPlot | (optional) logical. Default TRUE. Whether to plot the network. |
| clustMethod | (optional) character. Default "ward.D2". Clustering method for heatmap. See heatmap.2 |
| col | (optional) Color palette |
| distType | (optional) Distance type. Used only if specified explicitly. Otherwise, 1-cor is used. See dist , hclust |
| assignedClusters | vector integer or character. Default NULL. Cluster assignment of models. |
| corMethod | (optional) character. Default "spearman". Correlation method for distance function. |
| ... | Other arguments |

Value

RacipeSE object

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#),

Examples

```

data("demoCircuit")
## Not run:
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 20,

```

```
integrateStepSize = 0.1, simulationTime = 30)
rSet <- sracipePlotData(rSet)

## End(Not run)
```

sracipePlotParamBifur *Parameter bifurcation plots*

Description

Plot the expression of the genes against parameter values to understand the effect of parameters on the gene expressions.

Usage

```
sracipePlotParamBifur(
  .object,
  paramName,
  data = NULL,
  paramValue = NULL,
  assignedClusters = NULL,
  plotToFile = FALSE
)

## S4 method for signature 'RecipeSE'
sracipePlotParamBifur(
  .object,
  paramName,
  data = NULL,
  paramValue = NULL,
  assignedClusters = NULL,
  plotToFile = FALSE
)
```

Arguments

| | |
|------------------|---|
| .object | RecipeSE object generated by sracipeSimulate function. |
| paramName | character. The name of the parameter to be plotted. |
| data | (optional) dataframe. Default rSet geneExpression. The data to be plotted. For example, use rSet\$stochasticSimulations\$[noise] to plot the stochastic data. |
| paramValue | (optional) Dataframe. The parameter values if rSet\$params is not to be used. |
| assignedClusters | (optional) Dataframe. The cluster assignment of data. |
| plotToFile | (optional) logical. Default FALSE. Whether to save plots to a file. |

Value

none

Examples

```
data("demoCircuit")
## Not run:
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit, numModels = 100,
plots=FALSE, plotToFile = FALSE)
rSet <- sRACIPE::sracipeNormalize(rSet)
sracipePlotParamBifur(rSet, "G_A")

## End(Not run)
```

| | |
|-----------------|---|
| sracipeSimulate | <i>Simulate a gene regulatory circuit</i> |
|-----------------|---|

Description

Simulate a gene regulatory circuit using its topology as the only input. It will generate an ensemble of random models.

Usage

```
sracipeSimulate(
  circuit = "inputs/test.tpo",
  config = config,
  anneal = FALSE,
  knockOut = NA_character_,
  numModels = 2000,
  paramRange = 100,
  prodRateMin = 1,
  prodRateMax = 100,
  degRateMin = 0.1,
  degRateMax = 1,
  foldChangeMin = 1,
  foldChangeMax = 100,
  hillCoeffMin = 1L,
  hillCoeffMax = 6L,
  integrateStepSize = 0.02,
  simulationTime = 50,
  nIC = 1L,
  nNoise = 0L,
  simDet = TRUE,
  initialNoise = 50,
  noiseScalingFactor = 0.5,
  shotNoise = 0,
  scaledNoise = FALSE,
  outputPrecision = 12L,
  printStart = 50,
  printInterval = 10,
  stepper = "RK4",
  thresholdModels = 5000,
  plots = FALSE,
```

```

plotToFile = FALSE,
genIC = TRUE,
genParams = TRUE,
integrate = TRUE,
rkTolerance = 0.01,
timeSeries = FALSE,
nCores = 1L,
...
)

```

Arguments

| | |
|----------------------------|---|
| <code>circuit</code> | data.frame or character. The file containing the circuit or |
| <code>config</code> | (optional) List. It contains simulation parameters like integration method (step-per) and other lists or vectors like <code>simParams</code> , <code>stochParams</code> , <code>hyperParams</code> , <code>options</code> , <code>thresholds</code> etc. The list <code>simParams</code> contains values for parameters like the number of models (<code>numModels</code>), simulation time (<code>simulationTime</code>), step size for simulations (<code>integrateStepSize</code>), when to start recording the gene expressions (<code>printStart</code>), time interval between recordings (<code>printInterval</code>), number of initial conditions (<code>nIC</code>), output precision (<code>outputPrecision</code>), tolerance for adaptive runge kutta method (<code>rkTolerance</code>), parametric variation (<code>paramRange</code>). The list <code>stochParams</code> contains the parameters for stochastic simulations like the number of noise levels to be simulated (<code>nNoise</code>), the ratio of subsequent noise levels (<code>noiseScalingFactor</code>), maximum noise (<code>initialNoise</code>), whether to use same noise for all genes or to scale it as per the median expression of the genes (<code>scaledNoise</code>), ratio of shot noise to additive noise (<code>shotNoise</code>). The list <code>hyperParams</code> contains the parameters like the minimum and maximum production and degradation of the genes, fold change, hill coefficient etc. The list <code>options</code> includes logical values like <code>annealing</code> (<code>anneal</code>), scaling of noise (<code>scaledNoise</code>), generation of new initial conditions (<code>genIC</code>), parameters (<code>genParams</code>) and whether to integrate or not (<code>integrate</code>). The user modifiable simulation options can be specified as other arguments. This list should be used if one wants to modify many settings for multiple simulations. |
| <code>anneal</code> | (optional) Logical. Default FALSE. Whether to use annealing for stochastic simulations. If TRUE, the gene expressions at higher noise are used as initial conditions for simulations at lower noise. |
| <code>knockOut</code> | (optional) List of character or vector of characters. Simulation after knocking out one or more genes. To knock out all the genes in the circuit, use <code>knockOut = "all"</code> . If it is a vector, then all the genes in the vector will be knocked out simultaneously. |
| <code>numModels</code> | (optional) Integer. Default 2000. Number of random models to be simulated. |
| <code>paramRange</code> | (optional) numeric (0-100). Default 100. The relative range of parameters (production rate, degradation rate, fold change). |
| <code>prodRateMin</code> | (optional) numeric. Default 1. Minimum production rate. |
| <code>prodRateMax</code> | (optional) numeric. Default 100. Maximum production rate. |
| <code>degRateMin</code> | (optional) numeric. Default 0.1. Minimum degradation rate. |
| <code>degRateMax</code> | (optional) numeric. Default 1. Maximum degradation rate. |
| <code>foldChangeMin</code> | (optional) numeric. Default 1. Minimum fold change for interactions. |
| <code>foldChangeMax</code> | (optional) numeric. Default 100. Maximum fold change for interactions. |

| | |
|--------------------|--|
| hillCoeffMin | (optional) integer. Default 1. Minimum hill coefficient. |
| hillCoeffMax | (optional) integer. Default 6. Maximum hill coefficient. |
| integrateStepSize | (optional) numeric. Default 0.02. step size for integration using "EM" and "RK4" steppers. |
| simulationTime | (optional) numeric. Total simulation time. |
| nIC | (optional) integer. Default 1. Number of initial conditions to be simulated for each model. |
| nNoise | (optional) integer. Default 0. Number of noise levels at which simulations are to be done. Use nNoise = 1 if simulations are to be carried out at a specific noise. If nNoise > 0, simulations will be carried out at nNoise levels as well as for zero noise. "EM" stepper will be used for simulations and any argument for stepper will be ignored. |
| simDet | (optional) logical. Default TRUE. Whether to simulate at zero noise as well also when using nNoise > 0. |
| initialNoise | (optional) numeric. Default 50/sqrt(number of genes in the circuit). The initial value of noise for simulations. The noise value will decrease by a factor noiseScalingFactor at subsequent noise levels. |
| noiseScalingFactor | (optional) numeric (0-1) Default 0.5. The factor by which noise will be decreased when nNoise > 1. |
| shotNoise | (optional) numeric. Default 0. The ratio of shot noise to additive noise. |
| scaledNoise | (optional) logical. Default FALSE. Whether to scale the noise in each gene by its expected median expression across all models. If TRUE the noise in each gene will be proportional to its expression levels. |
| outputPrecision | (optional) integer. Default 12. The decimal point precision of the output. |
| printStart | (optional) numeric (0-simulationTime). Default simulationTime. To be used only when timeSeries is TRUE. The time from which the output should be recorded. Useful for time series analysis and studying the dynamics of a model for a particular initial condition. |
| printInterval | (optional) numeric (integrateStepSize- simulationTime - printStart). Default 10. The separation between two recorded time points for a given trajectory. To be used only when timeSeries is TRUE. |
| stepper | (optional) Character. Stepper to be used for integrating the differential equations. The options include "EM" for Euler-Maruyama O(1), "RK4" for fourth order Runge-Kutta O(4) and "DP" for adaptive stepper based Dormand-Prince algorithm. The default method is "RK4" for deterministic simulations and the method defaults to "EM" for stochastic simulations. |
| thresholdModels | (optional) integer. Default 5000. The number of models to be used for calculating the thresholds for genes. |
| plots | (optional) logical Default FALSE. Whether to plot the simulated data. |
| plotToFile | (optional) Default FALSE. Whether to save the plots to a file. |
| genIC | (optional) logical. Default TRUE. Whether to generate the initial conditions. If FALSE, the initial conditions must be supplied as a dataframe to circuit\$ic. |
| genParams | (optional) logical. Default TRUE. Whether to generate the parameters. If FALSE, the parameters must be supplied as a dataframe to circuit\$params. |

| | |
|--------------------------|--|
| <code>integrate</code> | (optional) logical. Default TRUE. Whether to integrate the differential equations or not. If FALSE, the function will only generate the parameters and initial conditions. This can be used iteratively as one can first generate the parameters and initial conditions and then modify these before using these modified values for integration. For example, this can be used to knockOut genes by changing the production rate and initial condition to zero. |
| <code>rkTolerance</code> | (optional) numeric. Default 0.01. Error tolerance for adaptive integration method. |
| <code>timeSeries</code> | (optional) logical. Default FALSE. Whether to generate time series for a single model instead of performing RACIPE simulations. |
| <code>nCores</code> | (optional) integer. Default 1. Number of cores to be used for computation. Utilizes <code>multiprocess</code> from <code>doFuture</code> package. Will not work in Rstudio. |
| <code>...</code> | Other arguments |

Value

RacipeSE object. RacipeSE class inherits `SummarizedExperiment` and contains the circuit, parameters, initial conditions, simulated gene expressions, and simulation configuration. These can be accessed using corresponding getters.

Related Functions

[sracipeSimulate](#), [sracipeKnockDown](#), [sracipeOverExp](#), [sracipePlotData](#)

Examples

```
data("demoCircuit")
rSet <- sRACIPE::sracipeSimulate(circuit = demoCircuit)
```

Index

- * **datasets**
 - configData, 7
 - CoupledToggleSwitchSA, 7
 - demoCircuit, 8
 - EMT1, 9
 - EMT2, 9
 - .ModelPvalue, 3
 - .NthMin, 4
 - .PermutedVar, 4
 - .RacipeSE (RacipeSE-class), 11
 - .SimulatedPValueAbs, 5
 - .SimulatedVarPValue, 5
 - .loadNetworkFile, 2
- annotation, RacipeSE-method, 6
- annotation<-, RacipeSE, ANY-method, 6
- configData, 7
- CoupledToggleSwitchSA, 7
- demoCircuit, 8
- densityPlot, 8
- dist, 25
- EMT1, 9
- EMT2, 9
- hclust, 17, 25
- heatmap.2, 25
- RacipeSE, 10
- RacipeSE-class, 11
- sRACIPE, 11
- sracipeCircuit, 10, 12
- sracipeCircuit, RacipeSE-method (sracipeCircuit), 12
- sracipeCircuit-set (sracipeCircuit<-), 13
- sracipeCircuit<-, 13
- sracipeCircuit<-, RacipeSE-method (sracipeCircuit<-), 13
- sracipeConfig, 14
- sracipeConfig, RacipeSE-method (sracipeConfig), 14
- sracipeConfig-set (sracipeConfig<-), 14
- sracipeConfig<-, 14
- sracipeConfig<-, RacipeSE-method (sracipeConfig<-), 14
- sracipeGenParamNames, 15
- sracipeGetTS, 15
- sracipeGetTS, RacipeSE-method (sracipeGetTS), 15
- sracipeHeatmapSimilarity, 8, 16, 17
- sracipeIC, 10, 17
- sracipeIC, RacipeSE-method (sracipeIC), 17
- sracipeIC-set (sracipeIC<-), 18
- sracipeIC<-, 18
- sracipeIC<-, RacipeSE-method (sracipeIC<-), 18
- sracipeKnockDown, 8, 12, 13, 17, 19, 20, 22, 24, 25, 30
- sracipeKnockDown, RacipeSE-method (sracipeKnockDown), 19
- sracipeNormalize, 20
- sracipeNormalize, RacipeSE-method (sracipeNormalize), 20
- sracipeOverExp, 8, 12, 13, 17, 20, 21, 22, 24, 25, 30
- sracipeOverExp, RacipeSE-method (sracipeOverExp), 21
- sracipeParams, 10, 22
- sracipeParams, RacipeSE-method (sracipeParams), 22
- sracipeParams-set (sracipeParams<-), 23
- sracipeParams<-, 23
- sracipeParams<-, RacipeSE-method (sracipeParams<-), 23
- sracipePlotCircuit, 23
- sracipePlotCircuit, RacipeSE-method (sracipePlotCircuit), 23
- sracipePlotData, 8, 12, 13, 17, 20, 22, 24, 24, 25, 30
- sracipePlotData, RacipeSE-method (sracipePlotData), 24
- sracipePlotParamBifur, 26
- sracipePlotParamBifur, RacipeSE-method

(`sracipePlotParamBifur`), [26](#)
`sracipeSimulate`, [8](#), [10](#), [12](#), [13](#), [17](#), [19–22](#),
[24–26](#), [27](#), [30](#)
`SummarizedExperiment`, [10](#), [11](#)